



AMP-440

40 Watt Two Zone Amplifier



Perfect for small home theaters, multi-room installations, or as a compliment to our 12 channel power amplifiers.

The TruAudio AMP-440 can power a soundbar or speakers while staying well hidden. It delivers outstanding sound quality and efficiency – in a thin and compact form factor. Plus it has A/B switching with selectable priority and IR control. Flexible mounting options include in-wall mounting using our recessed can (AMP-CAN), on-wall using the supplied brackets, or rack mounting using our AMP-440-BRACKET.

Features

- Thin and compact 4 channel, dual zone amplifier
- Powerful 4 x 40W output, bridgeable to 2 x 80W
- Thoughtful combination of inputs and outputs includes A/B switching and volume tracking output
- One of the thinnest TV amps on the market
- Internal power supply and removable power cord for easy installations
- IR port with included receiver “eye” for hidden installations
- Master volume can be controlled at the chassis or with remote, included
- Mounting options include rack mount, on-wall, and in-wall (with optional recessed box)





AMP-440

40 Watt Two Zone Amplifier

Specifications

Channels:	4 Channels, 2 Zones
Continuous Power:	40 watts/ch @ 8 ohms
Bridged Power Output:	80 watts/ch @ 4 ohms
Power Supply:	115v / 230v
Total Harmonic Distortion:	0.01%
Signal to Noise Ratio:	>-90dB (A Weighted)
Dimensions (HWD):	1.5" (39mm) H 8.9" (225mm) W 12.4" (316mm) D
Class:	D
Certification:	ETL, CE, C-Tick

